

PRODUCT-DETAILS

# S201-B6

# S201-B6 Miniature Circuit Breaker - 1P - B - 6 A



General Information	
Extended Product Type	S201-B6
Product ID	2CDS251001R0068
EAN	401677946490
Catalog Description	S201-B6 Miniature Circuit Breaker - 1P - B - 6 A
Long Description	System pro M compact S200 miniature circuit breakers are current limiting. They have two different tripping mechanisms, the delayed thermal tripping mechanism for overload protection and the electromechanic tripping mechanism for short circuit protection. They are available in different characteristics (B,C,D,K,Z), configurations (1P,1P+N,2P,3P,3P+N,4P), breaking capacities (up to 6 kA at 230/400 V AC) and rated currents (up to 63A). All MCBs of the product range S200 comply with IEC/EN 6098-1, IEC/EN 60947-2, UL 1077 allowing the use for residential, commercial and industrial applications. Bottom-fitting auxiliary contact can be mounted on S200 to save 50% space

ABB EcoSolutions Yes

#### Circular Value

Circular Design Principles
Recyclability Rate

Design for Closing Resource Loops - Standard EN45555 - 87.8 %

Offered with Extended Product Durability

© 2024 ABB. All rights reserved.

2024/01/29

Subject to change without notice

:£.	عti	 

Offered with Takeback Services	Take Back for Recyclin		
End of Life Instructions	9AKK108468A3132		

## Eco Transparency

Environmental Product 9AKK108467A7832 Declaration - EPD

Tech	nical

Technical		
Standards		IEC/EN 60898-1 IEC/EN 60947-2 UL 1077
Tripping Characteristic		В
Rated Operational Voltage		acc. to IEC 60898-1 230 / 400 V AC acc. to IEC 60898-1 230 V acc. to IEC 60947-2 230 V AC
Operational Voltage		Maximum (Incl. Tolerance) 253 V AC Maximum (Incl. Tolerance) 72 V DC Minimum 12 V AC Minimum 12 V DC
Rated Insulation Voltage (U <sub>i</sub> )		acc. to IEC/EN 60664-1 440 V
Rated Impulse Withstand Voltage (U <sub>imp</sub> )		4 kV at 2000 m 5 kV at Sea Level 6.2 kV
Dielectric Test Voltage		50/60 Hz, 1 min: 2 kV
Input Voltage Type		AC/DC
Rated Current (I <sub>n</sub> )		6 A
Rated Short-Circuit Capacity		(AC) 6 kA (DC) 6 kA (230 / 400 V AC) 6 kA (230 V) 6 kA (400 V) 6 kA
Rated Ultimate Short-Circuit Breaking Capacity (I <sub>cu</sub> )		(133 V AC) 20 kA (230 V AC) 10 kA (24 V DC) 20 kA (60 V DC) 10 kA (230 V) 10 kA (400 V) 10 kA
Rated Conditional Short- Circuit Current (I <sub>nc</sub> )		(230 V) 10 kA (400 V) 10 kA
Rated Service Short- Circuit Breaking Capacity (I <sub>cs</sub> )		(133 V AC) 15 kA (230 V AC) 7.5 kA
Frequency (f)		50 Hz
Rated Frequency (f)		50 / 60 Hz 50 60 Hz
Power Loss		2 W at Rated Operating Conditions per Pole 2 W
Power Supply Connection		Arbitrary
Contact Position Indication		Red ON / Green OFF
Energy Limiting Class		3
Electrical Endurance		20000 AC cycle
Mechanical Endurance		20000 cycle
Number of Poles		1
© 2024 ABB. All rights recorded	2024/01/20	Cubinet to about

Number of Protected Poles	1
Overvoltage Category	III
Tightening Torque	2.8 N·m
Mounting Type	DIN-Rail
Screw Terminal Type	Failsafe Bi-directional Cylinder-lift Terminal
Actuator Marking	1/0
Actuator Material	Insulation Group II, Black, Sealable
Housing Material	Insulation Group II, RAL 7035
Mounting on DIN Rail	TH35-15 (35 x 15 mm Mounting Rail) acc. to IEC 60715 TH35-7.5 (35 x 7.5 mm Mounting Rail) acc. to IEC 60715
Mounting Position	any
Recommended Screw Driver	Pozidriv 2
Accessories Available	Yes
Connecting Capacity	Busbar 10 / 10 mm² Flexible with Ferrule 0.75 25 mm² Flexible 0.75 25 mm² Rigid 0.75 35 mm² Rigid 0.75 35 mm² Stranded 0.75 35 mm²
Installation Size	acc. to DIN 43880 1
Wire Stripping Length	12.5 mm
Terminal Type	Screw Terminals

Material Compliance	
RoHS Information	2CDK403001D0607
RoHS Status	Following EU Directive 2011/65/EU and Amendment 2015/863 July 22, 2019
RoHS Date	0335
REACH Declaration	No declaration needed
Conflict Minerals Reporting Template (CMRT)	9AKK108468A3363
SCIP	e6800e55-46b1-49a3-881b-0f66d0e903ad Germany (DE)

Environmental	
Ambient Air Temperature	Operation -25 +55 °C Storage -40 +70 °C
Reference Ambient Air Temperature	30 °C
Degree of Protection	IP20 IP40 Enclosure with Cover IP40
Pollution Degree	3
Environmental Conditions	28 cycles with 55 °C / 90-96 % and 25 °C / 95-100 %
Resistance to Vibrations	20 Cycles with Load 0.8 ln: 5g 5 150 5 Hz
Resistance to Shock acc. to IEC 60068-2-27	25g 2 shocks 13 ms

## Technical UL/CSA

Maximum Operating Voltage UL/CSA	60 V DC 480Y/277 V AC
Interrupting Rating acc. to UL1077	(277 V AC) 6 kA (60 V DC) 10 kA (120 V) 10 kA
Connecting Capacity UL/CSA	Busbar 18-8 AWG Conductor 18-4 AWG
Tightening Torque UL/CSA	18 in·lb
Dimensions	
Width in Number of Modular Spacings	1
Product Net Width	17.5 mm
Product Net Height	88 mm
Product Net Depth / Length	69 mm
Product Net Weight	0.125 kg
Pole Net Weight	0.125 kg
Built-In Depth (t <sub>2</sub> )	69 mm
Dimension Diagram	2CDC022007F0010
Container Information	
Package Level 1 Units	carton 10 piece
Package Level 1 Width	92 mm
Package Level 1 Height	80 mm
Package Level 1 Depth / Length	183 mm
Package Level 1 Gross Weight	1.295 kg
Package Level 1 EAN	4016779606769
Package Level 2 Units	carton 120 piece
Package Level 2 Width	275 mm
Package Level 2 Height	210 mm
Package Level 2 Depth / Length	395 mm
Package Level 2 Gross Weight	14.8 kg
Package Level 2 EAN	4016779970594
Ordering	
Minimum Order Quantity	1 piece
E-Number (Finland)	3210106
E-Number (Sweden)	2100400
Certificates and Declarations	
Certification Agency	EN IEC
	ÜL

Declaration of Conformity - CE	2CDK403001D0607
Declaration of Conformity - UKCA	9AKK108467A5053
I <sup>2</sup> t Characteristic	9AKK107992A5102
Installation	
Instructions and Manuals	2CDS207104P0002
Popular Downloads	
Data Sheet, Technical Information	9AKK107991A8329
I²t Characteristic	9AKK107992A5102
Classifications	
ETIM 8	EC000042 - Miniature circuit breaker (MCB)
ETIM 9	EC000042 - Miniature circuit breaker (MCB)
WEEE Category	5. Small Equipment (No External Dimension More Than 50 cm)
WEEE B2C / B2B	Business To Business
CN8	8536 20 10
UNSPSC	39121603
eClass	V11.0 : 27141901
IDEA Granular Category Code (IGCC)	4897 >> Miniature circuit breakers
Object Classification Code	F

#### Accessories

Dec   Dec	Identifier	Description	Туре	Quantity	Unit Of Measure
2CDS200970R0001         \$2.H01 Auxiliary Contact         \$2.H01         1         piece           2CDS200970R0002         \$2.H10 Auxiliary Contact         \$2.H10         1         piece           2CDS200936R0001         \$2.H11. Auxiliary Contact         \$2.H11.         1         piece           2CDS200936R0002         \$2.H20. Auxiliary Contact         \$2.H20.1         1         piece           2CDS200936R0003         \$2.H2. Auxiliary Contact         \$2.H02.1         1         piece           2CDS200946R0001         \$2.H6.11R Auxiliary Contact         \$2.H6.11R         1         piece           2CDS200946R0002         \$2.H6.20R Auxiliary Contact         \$2.H6.20R         1         piece           2CDS200946R0003         \$2.H6.20R Auxiliary Contact         \$2.H6.20R         1         piece           2CDS20095R0002         \$2.H6.20R Auxiliary Contact         \$2.H6.20R         1         piece           2CDS20096R0003         \$2.H6.20R Auxiliary Contact         \$2.H6.20R         1         piece           2CDS20099R0001         \$2.H6.20R Auxiliary Contact         \$2.H6.20R         1         piece           2CSS200911R0001         \$2.H6.20R Auxiliary Contact         \$2.H6.20R         1         piece           2CSS200911R0001         \$2.H6.20R Auxiliary Cont	2CDS200922R0001	S2C-S/H6R Signal / Auxiliary Contact	S2C-S/H6R	1	piece
2CDS200970R0002         S2C-H10 Auxiliary Contact         S2C-H10 I         1 piece           2CDS200936R0001         \$2C-H11L Auxiliary Contact         \$2C-H11L I         1 piece           2CDS200936R0002         \$2C-H20L Auxiliary Contact         \$2C-H20L I         1 piece           2CDS200936R0003         \$2C-H02L Auxiliary Contact         \$2C-H6-11R I         1 piece           2CDS200946R0001         \$2C-H6-11R Auxiliary Contact         \$2C-H6-11R I         1 piece           2CDS200946R0002         \$2C-H6-20R Auxiliary Contact         \$2C-H6-20R I         1 piece           2CDS200946R0003         \$2C-H6-20R Auxiliary Contact         \$2C-H6-20R I         1 piece           2CDS200996R0001         \$2C-H3 Shunt Trip         \$2C-A1 I         1 piece           2CDS20099R0001         \$2C-A1 Shunt Trip         \$2C-A2 I         1 piece           2CSS20091R0001         \$2C-A2 A1 CUndervoltage Release \$2C-UA 12 DC I         1 piece           2CSS20091R0001         \$2C-UA 24 AC Undervoltage Release \$2C-UA 24 AC I         1 piece           2CSS20091R0003         \$2C-UA 24 AC Undervoltage Release \$2C-UA 24 AC I         1 piece           2CSS20091R0004         \$2C-UA 24 DC Undervoltage Release \$2C-UA 24 AC I         1 piece           2CSS20091R0003         \$2C-UA 240 CUndervoltage Release \$2C-UA 24 AC I         1 piece <tr< td=""><td>2CDS200912R0001</td><td>S2C-H6R Auxiliary Contact</td><td>S2C-H6R</td><td>1</td><td>piece</td></tr<>	2CDS200912R0001	S2C-H6R Auxiliary Contact	S2C-H6R	1	piece
2CDS200936R0001   S2C-H11L Auxiliary Contact   S2C-H11L   1   piece	2CDS200970R0001	S2C-H01 Auxiliary Contact	S2C-H01	1	piece
2CDS200936R0002         S2C-H20L Auxiliary Contact         S2C-H20L         1         piece           2CDS200936R0003         S2C-H02L Auxiliary Contact         S2C-H02L         1         piece           2CDS200946R0001         S2C-H6-11R Auxiliary Contact         S2C-H6-11R         1         piece           2CDS200946R0002         S2C-H6-20R Auxiliary Contact         S2C-H6-20R         1         piece           2CDS200946R0003         S2C-H6-20R Auxiliary Contact         S2C-H6-02R         1         piece           2CDS200999R0001         S2C-A1 Third Sylvant Trip         S2C-A1         1         piece           2CDS200999R0002         S2C-A2 Shunt Trip         S2C-A2         1         piece           2CSS200911R0001         S2C-UA 24 AC Undervoltage Release S2C-UA 24 AC         1         piece           2CSS200911R0002         S2C-UA 48 AC Undervoltage Release S2C-UA 48 AC         1         piece           2CSS200911R0003         S2C-UA 200 AC Undervoltage Release S2C-UA 48 AC         1         piece           2CSS200911R0004         S2C-UA 230 AC Undervoltage Release S2C-UA 24 AC         1         piece           2CSS200911R0005         S2C-UA 2400 AC Undervoltage Release S2C-UA 24 DC         1         piece           2CSS200911R0006         S2C-UA 2400 AC Undervoltage Release S2C-UA 24 DC </td <td>2CDS200970R0002</td> <td>S2C-H10 Auxiliary Contact</td> <td>S2C-H10</td> <td>1</td> <td>piece</td>	2CDS200970R0002	S2C-H10 Auxiliary Contact	S2C-H10	1	piece
Section	2CDS200936R0001	S2C-H11L Auxiliary Contact	S2C-H11L	1	piece
2CDS200946R0001         S2C-H6-11R Auxiliary Contact         S2C-H6-11R         1         piece           2CDS200946R0002         S2C-H6-20R Auxiliary Contact         S2C-H6-20R         1         piece           2CDS200946R0003         S2C-H6-02R Auxiliary Contact         S2C-H6-02R         1         piece           2CDS200999R0001         S2C-A1 Shunt Trip         S2C-A1         1         piece           2CDS20099R0002         S2C-A2 Shunt Trip         S2C-A2         1         piece           2CSS200911R0001         S2C-UA 12 DC Undervoltage Release S2C-UA 24 AC         1         piece           2CSS200911R0002         S2C-UA 24 AC Undervoltage Release S2C-UA 4AC         1         piece           2CSS200911R0003         S2C-UA 24 AC Undervoltage Release S2C-UA 4AC         1         piece           2CSS200911R0004         S2C-UA 48 AC Undervoltage Release         S2C-UA 4BAC         1         piece           2CSS200911R0005         S2C-UA 230 AC Undervoltage Release         S2C-UA 400         AC         1         piece           2CSS200911R0006         S2C-UA 400 AC Undervoltage Release         S2C-UA 4D C         1         piece           2CSS200911R0007         S2C-UA 48 DC Undervoltage Release         S2C-UA 4B DC         1         piece           2CSS200911R0009	2CDS200936R0002	S2C-H20L Auxiliary Contact	S2C-H20L	1	piece
2CDS200946R0002         S2C-H6-20R Auxiliary Contact         S2C-H6-20R         1         piece           2CDS200946R0003         S2C-H6-02R Auxiliary Contact         S2C-H6-02R         1         piece           2CDS200909R0001         S2C-A1 Shunt Trip         S2C-A1         1         piece           2CDS20099B0002         S2C-A2 Shunt Trip         S2C-A2         1         piece           2CSS200911R0001         S2C-UA 12 DC Undervoltage Release S2C-UA 12 DC         1         piece           2CSS200911R0002         S2C-UA 24 AC Undervoltage Release S2C-UA 24 AC         1         piece           2CSS200911R0003         S2C-UA 48 AC Undervoltage Release S2C-UA 48 AC         1         piece           2CSS200911R0004         S2C-UA 200 AC Undervoltage Release         S2C-UA 410 AC AC AC         1         piece           2CSS200911R0005         S2C-UA 230 AC Undervoltage Release         S2C-UA 230 AC AC         1         piece           2CSS200911R0006         S2C-UA 24 DC Undervoltage Release S2C-UA 40 AC AC         1         piece           2CSS200911R0007         S2C-UA 24 DC Undervoltage Release S2C-UA 48 DC AC	2CDS200936R0003	S2C-H02L Auxiliary Contact	S2C-H02L	1	piece
2CDS200946R0003         S2C-H6-02R Auxiliary Contact         S2C-H6-02R         1         piece           2CDS200909R0001         S2C-A1 Shunt Trip         S2C-A1         1         piece           2CDS200909R0002         S2C-A2 Shunt Trip         S2C-A2         1         piece           2CSS200911R0001         S2C-UA 12 DC Undervoltage Release S2C-UA 12 DC         1         piece           2CSS200911R0002         S2C-UA 24 AC Undervoltage Release S2C-UA 24 AC         1         piece           2CSS200911R0003         S2C-UA 48 AC Undervoltage Release S2C-UA 48 AC         1         piece           2CSS200911R0004         S2C-UA 110 AC Undervoltage Release S2C-UA 48 AC         1         piece           2CSS200911R0005         S2C-UA 230 AC Undervoltage Release S2C-UA 230 AC         1         piece           2CSS200911R0006         S2C-UA 400 AC Undervoltage Release S2C-UA 24 DC         1         piece           2CSS200911R0007         S2C-UA 48 DC Undervoltage Release S2C-UA 24 DC         1         piece           2CSS200911R0009         S2C-UA 110 DC Undervoltage Release S2C-UA 48 DC         1         piece           2CSS200911R0010         S2C-UA 230 DC Undervoltage Release S2C-UA 230 DC         1         piece           2CSS20199R0013         S2C-CM2 330 DC Undervoltage Release S2C-UA 230 DC         1         pi	2CDS200946R0001	S2C-H6-11R Auxiliary Contact	S2C-H6-11R	1	piece
2CDS200909R0001         S2C-A1 Shunt Trip         S2C-A1         1         piece           2CDS200909R0002         S2C-A2 Shunt Trip         S2C-A2         1         piece           2CDS200911R0001         S2C-UA 12 DC Undervoltage Release S2C-UA 12 DC         1         piece           2CSS200911R0002         S2C-UA 24 AC Undervoltage Release S2C-UA 24 AC         1         piece           2CSS200911R0003         S2C-UA 48 AC Undervoltage Release S2C-UA 48 AC         1         piece           2CSS200911R0004         S2C-UA 110 AC Undervoltage Release S2C-UA 48 AC         1         piece           2CSS200911R0005         S2C-UA 230 AC Undervoltage Release S2C-UA 230 AC         1         piece           2CSS200911R0006         S2C-UA 400 AC Undervoltage Release S2C-UA 400 AC         1         piece           2CSS200911R0007         S2C-UA 24 DC Undervoltage Release S2C-UA 24 DC         1         piece           2CSS200911R0008         S2C-UA 48 DC Undervoltage Release S2C-UA 48 DC         1         piece           2CSS200911R0009         S2C-UA 230 DC Undervoltage Release S2C-UA 48 DC         1         piece           2CSS200911R0010         S2C-UA 230 DC Undervoltage Release S2C-UA 230 DC         1         piece           2CSS201997R0013         S2C-CMA 230 DC Undervoltage Release S2C-UA 110 piece         S2C-UA 230 pC Undervoltage	2CDS200946R0002	S2C-H6-20R Auxiliary Contact	S2C-H6-20R	1	piece
2CDS20099SR0002         SZC-A2 Shunt Trip         S2C-A2         1         piece           2CSS200911R0001         S2C-UA 12 DC Undervoltage Release S2C-UA 12 DC         1         piece           2CSS200911R0002         S2C-UA 24 AC Undervoltage Release S2C-UA 24 AC         1         piece           2CSS200911R0003         S2C-UA 48 AC Undervoltage Release S2C-UA 48 AC         1         piece           2CSS200911R0004         S2C-UA 110 AC Undervoltage Release AC         S2C-UA 230 AC Undervoltage Release         1         piece           2CSS200911R0005         S2C-UA 230 AC Undervoltage Release AC         1         piece           2CSS200911R0006         S2C-UA 400 AC Undervoltage Release S2C-UA 400 AC         1         piece           2CSS200911R0007         S2C-UA 24 DC Undervoltage Release S2C-UA 4D C         1         piece           2CSS200911R0008         S2C-UA 48 DC Undervoltage Release S2C-UA 4B DC         1         piece           2CSS200911R0009         S2C-UA 110 DC Undervoltage Release S2C-UA 4B DC         1         piece           2CSS200911R0010         S2C-UA 230 DC Undervoltage Release DC         1         piece           2CSS201997R0013         S2C-UA 230 DC Undervoltage Release DC         1         piece           2CSS203997R0013         S2C-CM2/3 Motor Operating Device S2C-CM1         1         piec	2CDS200946R0003	S2C-H6-02R Auxiliary Contact	S2C-H6-02R	1	piece
2CSS200911R0001         S2C-UA 12 DC Undervoltage Release S2C-UA 12 DC         1         piece           2CSS200911R0002         S2C-UA 24 AC Undervoltage Release S2C-UA 24 AC         1         piece           2CSS200911R0003         S2C-UA 48 AC Undervoltage Release S2C-UA 48 AC         1         piece           2CSS200911R0004         S2C-UA 110 AC Undervoltage Release S2C-UA 410 AC         1         piece           2CSS200911R0005         S2C-UA 230 AC Undervoltage Release AC         S2C-UA 230 AC         1         piece           2CSS200911R0006         S2C-UA 400 AC Undervoltage Release S2C-UA 24 DC         1         piece           2CSS200911R0007         S2C-UA 24 DC Undervoltage Release S2C-UA 24 DC         1         piece           2CSS200911R0008         S2C-UA 48 DC Undervoltage Release S2C-UA 48 DC         1         piece           2CSS200911R0009         S2C-UA 230 DC Undervoltage Release S2C-UA 48 DC         1         piece           2CSS200911R0010         S2C-UA 230 DC Undervoltage Release S2C-UA 24 DC         1         piece           2CSS201997R0013         S2C-UA 230 DC Undervoltage Release S2C-UA 230 DC         1         piece           2CSS203997R0013         S2C-CMA 30 DC Undervoltage Release S2C-UA 24 DC         1         piece           2CSS203999R0013         S2C-CMA Motor Operating Device S2C-CM1         1	2CDS200909R0001	S2C-A1 Shunt Trip	S2C-A1	1	piece
2CSS200911R0002         \$2C-UA 24 AC Undervoltage Release \$2C-UA 24 AC         1         piece           2CSS200911R0003         \$2C-UA 48 AC Undervoltage Release \$2C-UA 48 AC         1         piece           2CSS200911R0004         \$2C-UA 110 AC Undervoltage Release AC         \$2C-UA 110 AC Undervoltage Release AC         \$2C-UA 230 AC Undervoltage Release AC         1         piece           2CSS200911R0005         \$2C-UA 230 AC Undervoltage Release AC         \$2C-UA 230 AC AC Undervoltage Release AC         1         piece           2CSS200911R0006         \$2C-UA 400 AC Undervoltage Release AC         \$2C-UA 400 AC Undervoltage Release AC         1         piece           2CSS200911R0007         \$2C-UA 24 DC Undervoltage Release S2C-UA 24 DC         1         piece           2CSS200911R0008         \$2C-UA 48 DC Undervoltage Release S2C-UA 48 DC         1         piece           2CSS200911R0009         \$2C-UA 110 DC Undervoltage Release S2C-UA 48 DC         1         piece           2CSS200911R0010         \$2C-UA 230 DC Undervoltage Release S2C-UA 410 DC         1         piece           2CSS200919R0013         \$2C-UA 230 DC Undervoltage Release S2C-UA 230 DC         1         piece           2CSS20099R0013         \$2C-CM2/3 Motor Operating Device S2C-CM1         1         piece           2CSS200999R0013         \$2C-DH Mechanical tripping device S2C-DH 1 <t< td=""><td>2CDS200909R0002</td><td>S2C-A2 Shunt Trip</td><td>S2C-A2</td><td>1</td><td>piece</td></t<>	2CDS200909R0002	S2C-A2 Shunt Trip	S2C-A2	1	piece
2CSS200911R0003         S2C-UA 48 AC Undervoltage Release S2C-UA 48 AC         1         piece           2CSS200911R0004         S2C-UA 110 AC Undervoltage Release         S2C-UA 110 AC AC         1         piece           2CSS200911R0005         S2C-UA 230 AC Undervoltage Release         S2C-UA 230 AC DAC AC         1         piece           2CSS200911R0006         S2C-UA 400 AC Undervoltage Release         S2C-UA 400 AC DAC AC         1         piece           2CSS200911R0007         S2C-UA 24 DC Undervoltage Release S2C-UA 24 DC         1         piece           2CSS200911R0008         S2C-UA 48 DC Undervoltage Release S2C-UA 48 DC         1         piece           2CSS200911R0009         S2C-UA 110 DC Undervoltage Release         S2C-UA 110 DC         1         piece           2CSS200911R0010         S2C-UA 230 DC Undervoltage Release         S2C-UA 230 DC         1         piece           2CSS201997R0013         S2C-CM2/3 Motor Operating Device         S2C-CM1         1         piece           2CSS204997R0013         S2C-CM4 Motor Operating Device         S2C-CM4         1         piece           2CSS200998R0013         S2C-DH Mechanical Accessories         S2C-DH         1         piece           2CSS200999R0001         S2C-BP Mechanical tripping device         S2C-BP         1         piece <td>2CSS200911R0001</td> <td>S2C-UA 12 DC Undervoltage Release S</td> <td>S2C-UA 12 DC</td> <td>1</td> <td>piece</td>	2CSS200911R0001	S2C-UA 12 DC Undervoltage Release S	S2C-UA 12 DC	1	piece
2CSS200911R0004         \$2C-UA 110 AC Undervoltage Release         \$2C-UA 110 AC AC         1         piece           2CSS200911R0005         \$2C-UA 230 AC Undervoltage Release         \$2C-UA 230 AC         1         piece           2CSS200911R0006         \$2C-UA 400 AC Undervoltage Release         \$2C-UA 400 AC         1         piece           2CSS200911R0007         \$2C-UA 24 DC Undervoltage Release \$2C-UA 24 DC         1         piece           2CSS200911R0008         \$2C-UA 48 DC Undervoltage Release \$2C-UA 48 DC         1         piece           2CSS200911R0009         \$2C-UA 110 DC Undervoltage Release         \$2C-UA 110 DC         1         piece           2CSS200911R0010         \$2C-UA 230 DC Undervoltage Release         \$2C-UA 230 DC         1         piece           2CSS201997R0013         \$2C-CM 1 Motor Operating Device         \$2C-CM1         1         piece           2CSS204997R0013         \$2C-CM2/3 Motor Operating Device         \$2C-CM4         1         piece           2CSS20099R0013         \$2C-CM4 Motor Operating Device         \$2C-CM4         1         piece           2CSS200998R0010         \$2C-BP Mechanical Accessories         \$2C-DH         1         piece           2CSS200999R0001         \$2C-EST Plug-in base         \$2C-EST         1         piece	2CSS200911R0002	S2C-UA 24 AC Undervoltage Release	S2C-UA 24 AC	1	piece
2CSS200911R0005         S2C-UA 230 AC Undervoltage Release         AC AC AC         1 piece           2CSS200911R0006         S2C-UA 230 AC Undervoltage Release         S2C-UA 400 AC	2CSS200911R0003	S2C-UA 48 AC Undervoltage Release	S2C-UA 48 AC	1	piece
2CSS200911R0006         S2C-UA 230 AC Undervoltage Release         AC         1         piece           2CSS200911R0006         S2C-UA 400 AC Undervoltage Release         S2C-UA 400 AC Undervoltage Release         S2C-UA 24 DC         1         piece           2CSS200911R0007         S2C-UA 24 DC Undervoltage Release S2C-UA 24 DC         1         piece           2CSS200911R0008         S2C-UA 48 DC Undervoltage Release S2C-UA 48 DC         1         piece           2CSS200911R0009         S2C-UA 110 DC Undervoltage Release         S2C-UA 110 DC Undervoltage Release         S2C-UA 230 DC         1         piece           2CSS200911R0010         S2C-UA 230 DC Undervoltage Release         S2C-UA 230 DC         1         piece           2CSS201997R0013         S2C-CM1 Motor Operating Device         S2C-CM1         1         piece           2CSS204997R0013         S2C-CM2/3 Motor Operating Device         S2C-CM2/3         1         piece           2CSS204997R0013         S2C-CM4 Motor Operating Device         S2C-CM4         1         piece           3CSS20499R0001         S2C-BP Mechanical Accessories         S2C-DH         1         piece           3CSS20099R0001         S2C-BP Mechanical tripping device         S2C-BP         1         piece           3CCS20099R0001         S2C-SET Plug-in base	2CSS200911R0004	S2C-UA 110 AC Undervoltage Release		1	piece
2CSS200911R0000         S2C-UA 400 AC Undervoltage Release         AC         I         piece           2CSS200911R0007         \$2C-UA 24 DC Undervoltage Release \$2C-UA 24 DC         1         piece           2CSS200911R0008         \$2C-UA 48 DC Undervoltage Release \$2C-UA 48 DC         1         piece           2CSS200911R0009         \$2C-UA 110 DC Undervoltage Release DC         \$2C-UA 110 DC         1         piece           2CSS200911R0010         \$2C-UA 230 DC Undervoltage Release DC         \$2C-UA 230 DC         1         piece           2CSS201997R0013         \$2C-CM1 Motor Operating Device S2C-CM1         1         piece           2CSS204997R0013         \$2C-CM2/3 Motor Operating Device S2C-CM2/3         1         piece           2CSS204997R0013         \$2C-CM4 Motor Operating Device S2C-CM4         1         piece           3CSS204997R0013         \$2C-DH Mechanical Accessories S2C-DH         1         piece           3CSS200998R0001         \$2C-BP Mechanical tripping device S2C-BP         1         piece           2CSS20099R0001         \$2C-BP Mechanical tripping device S2C-BT         1         piece           2CDS200918R0001         \$2C-MT Hand Operated Neutral S2C-NT         1         piece           2CCA880100R0001         CMS-100PS Sensor CMS-100PS         1         piece	2CSS200911R0005	S2C-UA 230 AC Undervoltage Release		1	piece
2CSS200911R0008         S2C-UA 48 DC Undervoltage Release S2C-UA 48 DC         1         piece           2CSS200911R0009         S2C-UA 110 DC Undervoltage Release         S2C-UA 110 DC Undervoltage Release         S2C-UA 110 DC Undervoltage Release         S2C-UA 230 DC Undervoltage Release         1         piece           2CSS200911R0010         S2C-UA 230 DC Undervoltage Release         S2C-UA 230 DC Undervoltage Release         S2C-UA 230 DC Undervoltage Release         1         piece           2CSS201997R0013         S2C-CM1 Motor Operating Device         S2C-CM1 1         piece           2CSS204997R0013         S2C-CM2/3 Motor Operating Device         S2C-CM4 1         piece           3CSS204997R0013         S2C-DH Mechanical Accessories         S2C-DH 1         piece           3CSS200998R0013         S2C-DH Mechanical Fripping device         S2C-DH 1         piece           3CSS200998R0001         S2C-BP Mechanical tripping device         S2C-BP 1         piece           3CCS200998R0001         S2C-BC S	2CSS200911R0006	S2C-UA 400 AC Undervoltage Release		1	piece
2CSS200911R0009         S2C-UA 110 DC Undervoltage Release         S2C-UA 230 DC Undervoltage Release         S2C-UA 1         piece           2CSS203997R0013         S2C-CM2/3 Motor Operating Device S2C-CM1         S2C-CM4         1         piece           2CSS200998R0001         S2C-DH Mechanical tripping device S2C-DH         S2C-BP         1         piece           2CDS200918R0001         S2C-EST Plug-in base S2C-EST         S2C-EST         1         piece           2CCA880100R0001         S2C-EST Plug-in Device S2C-DT         CMS-100PS Sensor CMS-100	2CSS200911R0007	S2C-UA 24 DC Undervoltage Release S	S2C-UA 24 DC	1	piece
2CSS200911R0009         S2C-UA 230 DC Undervoltage Release         DC DC         1 piece           2CSS200911R0010         S2C-UA 230 DC Undervoltage Release         S2C-UA 230 DC Undervoltage Release         S2C-UA 230 DC Undervoltage Release         DC         1 piece           2CSS201997R0013         S2C-CM1 Motor Operating Device         S2C-CM2/3         1 piece           2CSS204997R0013         S2C-CM2/3 Motor Operating Device         S2C-CM4         1 piece           GHS2001901R0003         S2C-DH Mechanical Accessories         S2C-DH         1 piece           2CSS200998R0001         S2C-BP Mechanical tripping device         S2C-BP         1 piece           2CSS200999R0001         S2C-EST Plug-in base         S2C-EST         1 piece           2CDS200918R0001         S2C-NT Hand Operated Neutral         S2C-NT         1 piece           2CCA880100R0001         CMS-100PS Sensor         CMS-100PS         1 piece           2CCA880101R0001         CMS-101PS Sensor         CMS-101PS         1 piece	2CSS200911R0008	)911R0008 S2C-UA 48 DC Undervoltage Release S2C-UA 48 DC		1	piece
2CSS20091R0010         S2C-UA 230 DC Undervoltage Release         DC         I         piece           2CSS201997R0013         \$2C-CM1 Motor Operating Device         \$2C-CM2/3         1         piece           2CSS203997R0013         \$2C-CM2/3 Motor Operating Device         \$2C-CM2/3         1         piece           2CSS204997R0013         \$2C-CM4 Motor Operating Device         \$2C-CM4         1         piece           GHS2001901R0003         \$2C-DH Mechanical Accessories         \$2C-DH         1         piece           2CSS200998R0001         \$2C-BP Mechanical tripping device         \$2C-BP         1         piece           2CSS20099R0001         \$2C-EST Plug-in base         \$2C-EST         1         piece           2CDS200918R0001         \$2C-NT Hand Operated Neutral         \$2C-NT         1         piece           2CCA880100R0001         \$CMS-100PS Sensor         \$CMS-100PS         1         piece           2CCA880101R0001         \$CMS-101PS Sensor         \$CMS-101PS         1         piece	2CSS200911R0009	S2C-UA 110 DC Undervoltage Release		1	piece
2CSS203997R0013         S2C-CM2/3 Motor Operating Device         S2C-CM2/3         1         piece           2CSS204997R0013         S2C-CM4 Motor Operating Device         S2C-CM4         1         piece           GHS2001901R0003         S2C-DH Mechanical Accessories         S2C-DH         1         piece           2CSS200998R0001         S2C-BP Mechanical tripping device         S2C-BP         1         piece           2CSS200999R0001         S2C-EST Plug-in base         S2C-EST         1         piece           2CDS200918R0001         S2C-NT Hand Operated Neutral         S2C-NT         1         piece           2CCA880100R0001         CMS-100PS Sensor         CMS-100PS         1         piece           2CCA880101R0001         CMS-101PS Sensor         CMS-101PS         1         piece	2CSS200911R0010	S2C-UA 230 DC Undervoltage Release		1	piece
2CSS204997R0013         S2C-CM4 Motor Operating Device         S2C-CM4         1         piece           GHS2001901R0003         S2C-DH Mechanical Accessories         S2C-DH         1         piece           2CSS200998R0001         S2C-BP Mechanical tripping device         S2C-BP         1         piece           2CSS200999R0001         S2C-EST Plug-in base         S2C-EST         1         piece           2CDS200918R0001         S2C-NT Hand Operated Neutral         S2C-NT         1         piece           2CCA880100R0001         CMS-100PS Sensor         CMS-100PS         1         piece           2CCA880101R0001         CMS-101PS Sensor         CMS-101PS         1         piece	2CSS201997R0013	S2C-CM1 Motor Operating Device	S2C-CM1	1	piece
GHS2001901R0003         S2C-DH Mechanical Accessories         S2C-DH         1         piece           2CSS200998R0001         S2C-BP Mechanical tripping device         S2C-BP         1         piece           2CSS200999R0001         S2C-EST Plug-in base         S2C-EST         1         piece           2CDS200918R0001         S2C-NT Hand Operated Neutral         S2C-NT         1         piece           2CCA880100R0001         CMS-100PS Sensor         CMS-100PS         1         piece           2CCA880101R0001         CMS-101PS Sensor         CMS-101PS         1         piece	2CSS203997R0013	S2C-CM2/3 Motor Operating Device	S2C-CM2/3	1	piece
2CSS200998R0001         S2C-BP Mechanical tripping device         S2C-BP         1         piece           2CSS200999R0001         S2C-EST Plug-in base         S2C-EST         1         piece           2CDS200918R0001         S2C-NT Hand Operated Neutral         S2C-NT         1         piece           2CCA880100R0001         CMS-100PS Sensor         CMS-100PS         1         piece           2CCA880101R0001         CMS-101PS Sensor         CMS-101PS         1         piece	2CSS204997R0013	S2C-CM4 Motor Operating Device	S2C-CM4	1	piece
2CSS200999R0001         S2C-EST Plug-in base         S2C-EST         1         piece           2CDS200918R0001         S2C-NT Hand Operated Neutral         S2C-NT         1         piece           2CCA880100R0001         CMS-100PS Sensor         CMS-100PS         1         piece           2CCA880101R0001         CMS-101PS Sensor         CMS-101PS         1         piece	GHS2001901R0003	S2C-DH Mechanical Accessories	S2C-DH	1	piece
2CDS200918R0001         S2C-NT Hand Operated Neutral         S2C-NT         1         piece           2CCA880100R0001         CMS-100PS Sensor         CMS-100PS         1         piece           2CCA880101R0001         CMS-101PS Sensor         CMS-101PS         1         piece	2CSS200998R0001	S2C-BP Mechanical tripping device	S2C-BP	1	piece
2CCA880100R0001         CMS-100PS Sensor         CMS-100PS         1         piece           2CCA880101R0001         CMS-101PS Sensor         CMS-101PS         1         piece	2CSS200999R0001	S2C-EST Plug-in base	S2C-EST	1	piece
2CCA880101R0001 CMS-101PS Sensor CMS-101PS 1 piece	2CDS200918R0001	S2C-NT Hand Operated Neutral	S2C-NT	1	piece
	2CCA880100R0001	CMS-100PS Sensor	CMS-100PS	1	piece
2CCA880102R0001 CMS-102PS Sensor CMS-102PS 1 piece	2CCA880101R0001	CMS-101PS Sensor	CMS-101PS	1	piece
	2CCA880102R0001	CMS-102PS Sensor	CMS-102PS	1	piece

	gories	

 $Low\ Voltage\ Products\ and\ Systems\ \rightarrow\ Modular\ DIN\ Rail\ Products\ \rightarrow\ Miniature\ Circuit\ Breakers\ MCBs\ \rightarrow\ Miniature\ MCBs\ \rightarrow\ Miniature\$ 





