



Main

| | |
|--------------------------|---|
| Range | Spacial |
| Product name | Spacial SBM |
| Device application | Multi-purpose |
| Category | Industrial box |
| Device short name | SBM |
| Enclosure type | Flat face box |
| Enclosure nominal height | 200 mm |
| Enclosure nominal width | 400 mm |
| Enclosure nominal depth | 120 mm |
| Enclosure mounting | Wall mounted |
| Device composition | 1 x body 1 x cover 4 x cover screw |
| Body type | Single piece body folded and welded |
| Type of front cover | Plain door |
| Cover fixing | Half turn metal screw |
| Lock type | Outside sealed area : PZ2 screwdriver captive screw |
| Removable parts | Cover, by captive screws |

Complementary

| | |
|-------------------------------------|------------------------------|
| Material | Sheet steel |
| Surface finish | Polyester powder |
| Colour | Grey (RAL 7035) |
| Standards | IEC 62208 |
| Product certifications | LR DNV BV UL GL |
| IP degree of protection | IP66 IEC 60529 |
| IK degree of protection | IK10 conforming to IEC 62262 |
| Ambient air temperature for storage | -35...60 °C |
| Operating temperature | -35...80 °C |
| Product weight | 3.078 kg |

Offer Sustainability

| | |
|----------------------------------|--|
| Sustainable offer status | Green Premium product |
| RoHS (date code: YYWW) | Compliant - since 1241 - Schneider Electric declaration of conformity Schneider Electric declaration of conformity |
| REACH | Reference not containing SVHC above the threshold |
| Product environmental profile | Available |
| Product end of life instructions | Need no specific recycling operations |

Contractual warranty

| | |
|-----------------|-----------|
| Warranty period | 18 months |
|-----------------|-----------|

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.